

LeaksProtect Jeweller

Wireless water leak detector



Constant control. Instant notifications.

LeaksProtect Jeweller monitors for leaks 24/7 and notifies of an issue before it escalates into damage. Compact enough to fit almost anywhere, the detector protects vulnerable areas, including hard-to-reach places. If a washing machine leaks or a pipe bursts, the device instantly reports the incident and can trigger the Ajax WaterStop Jeweller valve to automatically shut off the water supply. The detector requires no mounting and works for years without maintenance.

An Ajax hub is required for operation.

Key features

- Four contact pairs for detecting water from any direction
- Quick, tool-free installation
- Up to 5 years of operation on pre-installed batteries
- Up to 250 detectors within a single system
- Fast connection to an Ajax system via QR code
- Remote control and configuration via Ajax apps
- Up to 1,300 m (4,250 ft) of secure two-way radio communication with an Ajax hub or range extender in open space

Instant detection of water leaks

Sleek and simple on the outside, LeaksProtect Jeweller delivers reliable protection. With contact pairs on all four sides, the device detects water from any direction and immediately reports a leak. Once the contacts dry out and open, the detector notifies users that the leak has stopped.





Tool-free installation

LeaksProtect Jeweller requires no disassembly, mounting, or battery installation. The detector is simply placed on the floor under a washing machine, dishwasher, bathtub, or any other leak-prone area. Compact and discreet, the device fits even in hard-to-reach places and is ready to operate immediately.

Compatibility with hubs and range extenders For detailed information, scan the QR code or follow the link:  ajax.systems/tools/devices-compatibility/?groups=leak-detectors	Communication with a hub or range extender Frequency bands 866.0–866.5 MHz 868.0–868.6 MHz 868.7–869.2 MHz 905.0–926.5 MHz 915.85–926.5 MHz 921.0–922.0 MHz Depends on the sales region Jeweller communication technology Wireless communication range 1,300 m 4,250 ft In open space		Features Detection time within 0.15 s Automation scenarios Tool-free installation LED indication The LED is placed under the Ajax logo on the enclosure and reports the detector’s states.
Power supply Battery 2 × AAA battery Pre-installed Battery life up to 5 years	Installation Operating temperature 0 °C to +50 °C 32 °F to 122 °F Operating humidity up to 100%	General Color white, black Dimensions¹ 62 × 62 × 14 mm 2.44" × 2.44" × 0.55" Weight 41 g 1.45 oz Protection class IP65 Tamper button	Complete set LeaksProtect Jeweller 2 × AAA battery (pre-installed) Quick start guide

¹ 59 × 59 × 14 mm (2.32" × 2.32" × 0.55") for white devices manufactured before May 2026 and black devices before July 2026.



For detailed information, scan the QR code or follow the link:
ajax.systems/support/devices/leaksprotect

-  support@ajax.systems
-  [@AjaxSystemsSupport_Bot](https://t.me/AjaxSystemsSupport_Bot)
-  ajax.systems